

# ZyXEL ES-3124PWR V3.60(TY.3)C0

## Release Note/Manual Supplement

---

**Date:** Sep. 21, 2005

This document describes the features in the ES-3124PWR product for its 3.60(TY.3)C0 release.

### **Support Platforms:**

---

ZyXEL ES-3124PWR V3.60(TY.3)C0 supports models: ZyXEL ES-3124PWR

### **Version:**

---

OS Version: V3.60(TY.3) | 09/21/2005 18:20:28

BootBase Version: V0.1 | 02/01/2005 16:33:32

### **Features:**

---

1. 24 Auto MDI/MDI-X 100BASE-TX ports with power over Ethernet support
2. 2 1000BASE-T ports for cascading
3. 2 1000BASE-T/SFP combo ports for uplink
4. 16K layer2 MAC addresses table
5. Support 32MB external packet buffer.
6. IEEE 802.1D transparent bridging
7. Port-based VLAN
8. IEEE 802.1Q tag-based VLAN
9. IGMP snooping
10. MAC filtering
11. Management through console, telnet, SNMP or web management
12. Firmware upgrade by FTP
13. Configuration saving and retrieving
14. Overheat detection
15. LED indications for link status
16. External power backup for internal power module failure
17. 9K jumbo frame support
18. Filtering/Mirroring by L2/L3/L4 rules
19. Bandwidth control by L2/L3/L4 rules
20. Egress traffic shaping per port at 64Kbps step
21. Private VLAN for port isolation
22. Double tagging
23. BPDU transparency.
24. SSHv1/SSHv2/SSL
25. Integrated multicast services.
26. Dual rate three colors.
27. ZyXEL EMS support.
28. Power management on PoE ports

### **Known Issues:**

---

1. Management port test fail in 100M long cable.
2. Management port has compatible issue with Cnet Pro 2000 network interface card.
3. The packets which destination address is marked in the filter setting will always send to port 1.
4. Symbol and dribble error packets will count into FCS error counter.

5. Filtering: In some special cases, setting one MAC with discard-source will cause device filter all packets with this MAC, ether source MAC or destination MAC.
6. Do not suggest cooperate LACP with RSTP more than ten ports.
7. Do not support tagged frame forwarding in the Port-Based VLAN.
8. If total PD power consumption is over power supply specification, the latter plugging PD wouldn't be powered over Ethernet.
9. If the contact between RJ45 and wire cable or the wire cable is unstable, the cable diagnostics maybe fail.

***Fix:***

---

- 1.

***Manufacturing Data:***

---

|                        |  |
|------------------------|--|
| ZyNOS Version          | : V3.60(TY.3)   09/21/2005 18:20:28                |
| Bootbase Version       | : V0.1   02/01/2005 16:33:32                       |
| Serial Number          | : xxxxxxxxxxxxxxxx                                 |
| Vendor Name            | : ZyXEL Communications Corp.                       |
| Product Model          | : ES-3124PWR                                       |
| ZyNOS Code Model       | : ES3124PWR  |
| HTP Code Model         | : Unknown  |
| ZyNOS ROM address      | : 50080000   |
| System Type            | : 10   |
| MAC Address            | : 001349000001                                     |
| Default Country Code   | : FF   |
| Boot Module Debug Flag | : 01   |
| RomFile Version        | : 84   |
| RomFile Checksum       | : ae79   |
| ZyNOS Checksum         | : 3a48   |
| SNMP MIB level & OID   | : 060102030405060708091011121314151617181920       |
| Main Feature Bits      | : C0   |
| Other Feature Bits     | :  |
|                        | D1 00 00 00 00 00 00 00 00-00 00 00 00 00 00 00 00 |
|                        | 00 00 00 00 00 00 00 00 00-00 41 13 00 00 00 00    |

## ***Firmware Upgrade:***

---

The ES-3124PWR uses FTP to upgrade firmware in run-time through its built-in FTP server. You can use any FTP client (for example, [ftp.exe](#) in Windows) to upgrade ES-3124PWR. The upgrade procedure is as follows:

### **Upgrade ES-3124PWR FW:**

```
C:\> ftp <ES-3124PWR IP address>
User : admin
Password: 1234
230 Logged in
ftp> put 360TY3C0.bin ras
ftp> bye
```

Where

- User name : the management user name, admin by default
- Password : the management password, 1234 by default
- 360TY3C0.bin : the name of firmware file you want to upgrade
- ras : the internal firmware name in ES-3124PWR

## ***Configuration Upgrade:***

---

The ES-3124PWR uses FTP to upgrade configuration in run-time through its built-in FTP server. You can use any FTP client (for example, [ftp.exe](#) in Windows) to upgrade ES-3124PWR. The upgrade procedure is as follows:

### **Upgrade ES-3124PWR configuration:**

```
C:\> ftp <ES-3124PWR IP address>
User : admin
Password: 1234
230 Logged in
ftp> put 360TY3C0.rom rom-0
ftp> bye
```

Where

- User name : the management user name, admin by default
- Password : the management password, 1234 by default
- 360TY3C0.rom : the name of configuration file you want to upgrade
- rom-0 : the internal configuration name in ES-3124PWR